

**METHOD FOR MANUFACTURING MEMORY WITH HIGH
CONDUCTIVITY BITLINE AND SHALLOW TRENCH ISOLATION
INTEGRATION**

Docket Number: G0807

Inventors:

Jeffrey P. Erhardt
Citizenship: USA
4355 Renasissance Dr., #112
San Jose, CA 95134

and

Kashmir S. Sahota
Citizenship: USA
43067 Scofield Court
Fremont, CA 94539

Contact: Mikio Ishimaru
(408) 738-0592

METHOD FOR MANUFACTURING MEMORY WITH HIGH CONDUCTIVITY BITLINE AND SHALLOW TRENCH ISOLATION INTEGRATION

BACKGROUND OF THE INVENTION

TECHNICAL FIELD

5 The present invention relates generally to semiconductor technology and more specifically to shallow trench isolation and bitline integration in MirrorBit® Flash memory.

BACKGROUND ART

Various types of memories have been developed in the past as electronic memory media for computers and similar systems. Such memories include electrically erasable programmable read only memory (EEPROM) and electrically programmable read only memory (EPROM). Each type of memory had advantages and disadvantages. EEPROM can be easily erased without extra exterior equipment but with reduced data storage density, lower speed, and higher cost. EPROM, in contrast, is less expensive and has greater density but lack erasability.

15 A newer type of memory called "Flash" EEPROM, or Flash memory, has become extremely popular because it combines the advantages of the high density and low cost of EPROM with the electrical erasability of EEPROM. Flash memory can be rewritten and can hold its contents without power. It is used in many portable electronic products, such as cell phone, portable computers, voice recorders, etc. as well as in many larger electronic systems,
20 such as cars, planes, industrial control systems, etc.

 In Flash memory, bits of information are programmed individually as in the older types of memory, such as dynamic random access memory (DRAM) and static random access memory (SRAM) memory chips. However, in DRAMs and SRAMs where individual bits can be erased one at a time, Flash memory must currently be erased in fixed multi-bit
25 blocks or sectors.

Conventionally, Flash memory is constructed of many Flash memory cells where a single bit is stored in each memory cell and the cells are programmed by hot electron injection and erased by Fowler-Nordheim tunneling. However, increased market demand has driven the development of Flash memory cells to increase both the speed and the density.

Newer Flash memory cells have been developed that allow more than a single bit to be stored in each cell.

One memory cell structure involves the storage of more than one level of charge to be stored in a memory cell with each level representative of a bit. This structure is referred to as a multi-level storage (MLS) architecture. Unfortunately, this structure inherently requires a great deal of precision in both programming and reading the differences in the levels to be able to distinguish the bits. If a memory cell using the MLS architecture is overcharged, even by a small amount, the only way to correct the bit error would be to erase the memory cell and totally reprogram the memory cell. The need in the MLS architecture to precisely control the amount of charge in a memory cell while programming also makes the technology slower and the data less reliable. It also takes longer to access or “read” precise amounts of charge. Thus, both speed and reliability are sacrificed in order to improve memory cell density.

An even newer technology allowing multiple bits to be stored in a single cell is known as “MirrorBit®” Flash memory has been developed. In this technology, a memory cell is essentially split into two identical (mirrored) parts, each of which is formulated for storing one of two independent bits. Each MirrorBit Flash memory cell, like a traditional Flash cell, has a gate with a source and a drain. However, unlike a traditional Flash cell in which the source is always connected to an electrical source and the drain is always connected to an electrical drain, each MirrorBit Flash memory cell can have the connections of the source and drain reversed during operation to permit the storing of two bits.

The MirrorBit Flash memory cell has a semiconductor substrate with implanted conductive bitlines. A multilayer storage layer, referred to as a “charge-trapping dielectric layer”, is formed over the semiconductor substrate. The charge-trapping dielectric layer can generally be composed of three separate layers: a first insulating layer, a charge-trapping layer, and a second insulating layer. Wordlines are formed over the charge-trapping dielectric layer perpendicular to the bitlines. Programming circuitry controls two bits per cell by applying a signal to the wordline, which acts as a control gate, and changing bitline connections such that one bit is stored by source and drain being connected in one arrangement and a complementary bit is stored by the source and drain being interchanged in another arrangement.

Programming of the cell is accomplished in one direction and reading is accomplished in a direction opposite that in which it is programmed.

One significant problem in memory devices is that the implanted conductive bitlines have a relatively high resistivity, which results in higher power requirements, and subsequent heat generation with reduced life expectancy, for the memory cell.

A second significant problem involves the large number of steps needed to form shallow trench isolation (STI). STI is used to electrically isolate the MirrorBit memory in the core region from the other devices in the peripheral area. It consists of trenches filled with an insulator material, such as silicon oxide, forming an electrical barrier to prevent interference between core and peripheral devices. Unfortunately, traditional STI construction requires a large number of processing steps, which are performed separately from those used to create devices in the core. With the prohibitive cost in equipment, time, and planning for each additional step, it is crucial to minimize the number of process steps.

A third significant problem is that, during implantation of the bitlines, dopant is subject to a scattering effect. The impact of the dopant on and in the semiconductor substrate causes the dopant ions to scatter at angles away from the direction of implantation so the ions not end up directly under the implantation region. As a result, when the bitline and dopant are annealed, the dopant diffuses over a wider region than desired. This severely limits how closely the bitlines can be placed and, thus, how small the memory device can be made.

A solution that would solve the above and other problems with implanted bitlines has been long sought but has long eluded those skilled in the art.

DISCLOSURE OF THE INVENTION

The present invention provides a method for manufacturing a Flash memory with high conductivity bitlines and shallow trench isolation integration. A hard mask layer is deposited over a substrate. A first photoresist is deposited over the hard mask layer, processed, and used to form a hard mask. The first photoresist is removed and the substrate is processed using the hard mask to form a core trench and a shallow trench isolation (STI) trench. The trenches are filled with an insulating material in an STI fill process. A second photoresist is deposited and processed to form a core mask over the STI trenches. Using the core mask, the insulating material is removed from the core trenches and the core mask is removed. A doped bitline material is deposited on the surface of the semiconductor, which fills the core trench. The surface of the semiconductor is planarized, inlaying insulating material and doped bitline material in the trenches. A thermal anneal outdiffuses the dopant from the doped bitline material into the substrate.

The present invention further provides high conductivity bitlines for Flash memory and a manufacturing method therefor.

The present invention also provides a method for manufacturing Flash memory, which integrates STI and bitline creation, resulting in fewer process steps.

5 The above and additional advantages of the present invention will become apparent to those skilled in the art from a reading of the following detailed description when taken in conjunction with the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 (PRIOR ART) is a plan view of a conventional MirrorBit Flash EEPROM;

10 FIG. 2 (PRIOR ART) is a circuit schematic of a portion of one of the M x N array cores of FIG. 1 (PRIOR ART);

FIG. 3 (PRIOR ART) is a plan view of a portion of one of the M x N array cores 104 of FIG. 1 (PRIOR ART);

5 FIG. 4 (PRIOR ART) is a cross-sectional isometric view of a typical MirrorBit Flash memory cell along the line 4--4 of FIG. 3 (PRIOR ART);

FIG. 5 is a substrate after a shallow trench isolation formation and fill process;

FIG. 6 is the structure of FIG. 6 after the creation of a core mask;

FIG. 7 is the structure of FIG. 7 after a core shallow trench isolation etch;

20 FIG. 8 is the structure of FIG. 8 after the core mask removal and doped bitline deposition;

FIG. 9 is the structure of FIG. 9 after planarization and thermal anneal processes;

FIG. 10 is a cross-sectional view of a Flash memory cell similar to a cross-sectional view along line 5--5 in FIG. 3 (PRIOR ART); and

FIG. 11 is shown a simplified process chart of the present invention.

25 BEST MODE FOR CARRYING OUT THE INVENTION

Referring now to FIG. 1 (PRIOR ART), therein is shown a plan view of a MirrorBit® Flash EEPROM 100, which commonly includes a semiconductor substrate 102 in which one or more high-density core regions and one or more low-density peripheral portions are formed. High-density core regions typically include one or more M x N array cores 104 of
30 individually addressable, substantially identical MirrorBit Flash memory cells. Low-density

peripheral portions typically include input/output (I/O) circuitry and programming circuitry for selectively addressing the individual memory cells. The programming circuitry is represented in part by and includes one or more x-decoders 108 and y-decoders 110, cooperating with I/O circuitry 106 for connecting the source, gate, and drain of selected addressed memory cells to predetermined voltages or impedances to effect designated operations on the memory cell, e.g., programming, reading, and erasing, and deriving necessary voltages to effect such operations.

The term "horizontal" as used in herein is defined as a plane parallel to the conventional plane or surface the semiconductor substrate 102 regardless of its orientation. The term "vertical" refers to a direction perpendicular to the horizontal as just defined. Terms, such as "on", "above", "below", "higher", "lower", "over", "under", "side" and "beside", are defined with respect to these horizontal and vertical planes. The term "processed" as used herein is defined to include one or more of the following: depositing or growing semiconductor materials, masking, patterning, photolithography, etching, implanting, removal, and/or stripping.

Referring now to FIG. 2 (PRIOR ART), therein is shown a circuit schematic of a portion of one of the M x N array cores 104 of FIG. 1 (PRIOR ART). The circuit schematic shows a line of memory cells 200, which includes memory cells 201 through 204 and which together can form an 8-bit word. Each of the memory cells 201 through 204 is connected to a wordline 206, which acts as a control gate. Each of the memory cells 201 through 204 has two associated bitlines with most of the memory cells having a common bitline. The memory cell 201 has associated bitlines 208 and 209; the memory cell 202 has associated bitlines 209 and 210; the memory cell 203 has associated bitlines 210 and 211; and the memory cell 204 has associated bitlines 211 and 212.

Depending upon a signal on the wordline and the connection of the bitlines in a memory cell to an electrical source or drain, the memory cells 201 through 204 are capable of writing, reading, and erasing bits at locations 215 through 222. For example, control of the bit at location 215 is achieved through connection of the drain to the bitline 208 and the source to the bitline 209. Similarly, control of the bit at location 216 is achieved through connection of the drain to the bitline 209 and the source to the bitline 208. Although adjacent memory cells share common bitlines, the adjacent memory cells do not interfere with each other because the memory cells are programmed one at a time and only one memory cell is active at a time while programming.

Referring now to FIG. 3 (PRIOR ART), therein is shown a plan view of a portion of one of the M x N array cores 104 of FIG. 1 (PRIOR ART). The semiconductor substrate 102 has a plurality of implanted bitlines 304 extending in parallel with a plurality of formed wordlines 302 extending in parallel and at right angles to the plurality of implanted bitlines 304. The wordlines 302 and bitlines 304 have contacts and interconnections (not shown) to the programming circuitry represented in part by x-decoders 108 and y-decoders 110 of FIG. 1 (PRIOR ART).

Referring now to FIG. 4 (PRIOR ART), therein is shown a cross-sectional isometric view of a typical MirrorBit Flash memory cell along the line 4--4 of FIG. 3 (PRIOR ART), such as a memory cell 400. The semiconductor substrate 102 is a p-doped silicon substrate with a threshold adjustment implant 402 of a p-type material, such as boron. The threshold adjustment implant 402 provides a region that is more heavily doped than the semiconductor substrate 102 itself and assists in the control of the threshold voltage of the memory cell 400.

A charge-trapping dielectric layer 404 is deposited over the semiconductor substrate 102. The charge-trapping dielectric layer 404 generally can be composed of three separate layers: a first insulating layer 406, a charge-trapping layer 408, and a second insulating layer 410. The first and second insulating layers 406 and 410 are of an oxide dielectric such as silicon dioxide (SiO_2) and the charge-trapping layer 408 is of a nitride dielectric such as silicon nitride (SiN). The oxide-nitride-oxide configuration is frequently referred to as a matter of convenience as an "ONO layer".

The bitlines 304 of FIG. 3 (PRIOR ART) are implanted under the charge-trapping dielectric layer 404 in the semiconductor substrate 102 as typified by first and second conductive bitlines 412 and 414. They are typically of an implanted n-type material, such as arsenic, and can include an oxide portion (not shown) in some embodiments. The first and second conductive bitlines 412 and 414 are spaced apart and define a volume between them with the threshold adjustment implant 402, which is a channel 416.

A material, such as polysilicon, is deposited over the charge-trapping dielectric layer 404, patterned, etched, and stripped resulting in a wordline 418. The wordline 418 is one of the wordlines 302 in FIG. 3 (PRIOR ART).

It is understood that the implementation of each step in manufacturing has associated processing steps including, but not limited to, patterning and masking, etching, depositing, implanting and/or stripping, all of which are commonly known to those having ordinary skill in the art.

For convenience, when looking at FIG. 4 (PRIOR ART), the wordline 418 is also referred to as the "control gate" and the bitlines 412 and 414 are designated as "left" and "right" bitlines. When the bitlines 412 and 414 are respectively connected to drain and source, they are also respectively referred to as "drain" and "source" and, when the bitlines 412 and 414 are respectively connected to source and drain, they are also respectively referred to as "source" and "drain". While the bits in a memory cell are generally referred to as "first" and "complementary" bits, for ease of explanation herein, the separate bits are respectively designated as "left" and "right" bits herein, with each bitline having a left and right bit.

During programming of a right bit, such as the right bit 420 of the bitline 412, the bitline 412 is the drain and the bitline 414 is the source. When the wordline 418 is positively charged as the control gate, electrical fields are generated that cause hot electron injection from the drain bitline 412 into the channel 416 and towards the wordline 418. The negatively charged electrons gain the most energy at the drain so they pass through the first insulating layer 406 and into the charge-trapping layer 408 where they are trapped because they do not have enough energy to pass through the second insulating layer 410. These trapped electrons are a bit of information, which is the right bit 420. The right bit 420 can be detected during "reads" and remains until it is "erased" by a negative charge applied to the control gate.

Similarly, during programming of a left bit, such as the left bit 422 of the bitline 412, the bitline 414 is the drain and the bitline 412 is the source. When the wordline 418 is positively charged as the control gate, electrical fields are generated that cause hot electron injection from the drain bitline 414 into the channel 416 and towards the wordline 418. The negatively charged electrons gain the most energy at the drain so they pass through the first insulating layer 406 and into the charge-trapping layer 408 where they are trapped because they do not have enough energy to pass through the second insulating layer 410. These trapped electrons are a bit of information, which is the left bit 422. The left bit 422 can be detected during "reads" and remains until it is "erased" by a negative charge applied to the control gate.

Because the charge-tapping layer 408 is also a dielectric material, generally silicon nitride, the electrons do not move or migrate between right and left so the two bits are independent of each other. Further, the right bit is affected by the electrons coming from the right drain and the left bit is affected by the electrons from the left drain connection so the interchanging of the source and drain do not significantly affect the bit next to the source

connection. Further, since the memory cell 400 is programmed individually, the source or drain connections will only effect bits 420 and 422; i.e., bits 424 and 426 would not be affected because the bitlines (not shown) to the left and right of bitlines 412 and 414 would not be connected to either source or drain.

5 Referring now to FIG. 5, therein is shown a cross-sectional view of a partially processed memory device 500 including a semiconductor substrate 502 having an optional patterned anti-reflective coating (ARC) 504 and a patterned photoresist 505 which form a photomask, shown as a dotted line. The photomask has been used to form a patterned hard mask 506 on the semiconductor substrate 502 and then been removed. The hard mask 506 covers a core region 508 and a peripheral region 510.

10 The hard mask 506 has been used to etch openings in the semiconductor substrate 502 to form core trenches 512-514 in the core region 508 and a shallow trench isolation (STI) region 515 between the core region 508 and the peripheral region 510.

15 Referring now to FIG. 6, therein is shown the partially processed memory device 500 of FIG. 5 after an STI fill process which forms an isolation material, such as silicon oxide or silicon nitride, into the core trenches 512-514, and the STI trench 516 to form respective core isolations 517-519 and STI 520.

20 Referring now to FIG. 7, therein is shown the partially processed memory device 500 of FIG. 6 after photoresist is deposited over the partially processed memory device 500 and patterned to form a core mask 522. The core mask 522 does not have to be critically dimensioned and exposes the core region 508 and covers peripheral region 510, including the STI 520.

25 Referring now to FIG. 8, therein is shown the partially processed memory device 500 of FIG. 7 after an etch removes the core isolations 517-519 in the core trenches 512-514. The core mask 522 protects the STI 520 and the insulating material is not removed.

30 Referring now to FIG. 9, therein is shown the partially processed memory device 500 of FIG. 8 after the core mask 522, the optional ARC 504, and the hard mask 506 are removed by a stripping process. A layer of doped, highly conductive, bitline material 524, such as doped polysilicon, has been deposited over the surface of the partially processed memory device 500 and in the core trenches 512- 514.

Referring now to FIG. 10, therein is shown the partially processed memory device 500 of FIG. 9 after the layer of doped, high conductivity, bitline material 524 and the STI 520 are planarized by a planarization technique, such as chemical-mechanical polishing (CMP)

process. The result is a planar surface with the doped, high conductivity material inlaid in the core trenches 512- 514.

To form high conductivity bitlines 521-523, a thermal annealing process is used to diffuse dopant 525 from the doped, high conductivity material into the semiconductor substrate 502 to provide required electrons in the same fashion as implanted bitlines.

It should be noted that in contrast to the implanted bitlines 412 and 414 in FIG. 4 (PRIOR ART), the high conductivity bitlines 521-523 are formed from the combination of highly conductive polysilicon and outdiffused dopant in the semiconductor substrate 502. These filled-trench bitlines have a lower resistivity and higher conductivity when compared to their implanted prior art counterparts. The term "high conductivity bitline" defines a bitline with a conductivity higher than that of a bitline in which a dopant is implanted into silicon and used alone as the conductive line.

As a further advantage, instead of separate STI construction steps and the bitline creation steps of masking, implantation, and mask-removal steps of the prior art, the current invention uses integration of the STI manufacturing steps to create the bitlines, resulting in fewer, less complicated process steps.

In addition, the spacing of the trench-filled bitlines can be very close together since the STI trench locations can be easily and extremely tightly controlled by masking. The degree of diffusion of the doping can be controlled by time and temperature so as to have the dopant very close to the implanted bitlines 412 and 414 to allow them to be much closer together.

Thereafter, a charge-trapping dielectric layer 528 and a wordline 530 are formed to substantially complete the Flash memory device 500.

Referring now to FIG. 11, therein is shown a simplified process chart 600 of the present invention which includes: providing semiconductor substrate 602; processing masks 604; forming trenches 606; depositing insulating material 608; forming a core mask 610; removing insulating material 612; removing the core mask 614; depositing doped conductive material 616; planarizing doped conductive material and insulating material 618; annealing doped conductive material to form bitlines 620; depositing charge-trapping layer 622; and forming wordlines 624.

Various implementations of dual bit memory cell and other semiconductor device architecture may be achieved according to one or more aspects of the present invention. In

particular, the invention is applicable to memory devices wherein both bits in a dual bit cell are used for data or information storage.

- 5 While the invention has been described in conjunction with a specific best mode, it is to be understood that many alternatives, modifications, and variations will be apparent to those skilled in the art in light of the foregoing description. Accordingly, it is intended to embrace all such alternatives, modifications, and variations that fall within the spirit and scope of the included claims. All matters hither-to-fore set forth or shown in the accompanying drawings are to be interpreted in an illustrative and non-limiting sense.

10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2